

30 Watt LED Emergency Driver

Multi-function Driver, it can be used as standard LED driver as well as an emergency LED driver, with 50,000hrs lifespan.

All in one design: constant current driver + efficient boosting + constant current recharging

Easy installation, simply plug-in, no maintenance

High transforming efficiency

Isolation safe design

High power factor

Reliable protection design in case of over load and over voltage

Smart automation differs between standard lighting and emergency lighting

Certification:SAA,GS, CB, CE,

Dimensions: 210mm x 40mm x 30mm

Power: 100~240V, 50/60Hz

Max Power Output : 30W

Current: 500 mA

Power Factor: 0.9

Charging Time: >5 hours

Emergency Time: 1-3 hours



Product Code: EMD-30